

DESCRIPTION




The SERIES8 cardioid collection is offered in three popular styles: headset, earworn, and lavalier. The cardioid pick up pattern is ideal in applications when there is more than one mic being used, in live performances, and in some recording situations. A unique benefit of the SERIES8 cardioid headset and earworn microphones is that the capsule is especially miniaturized and there is no need to force the mic directly in front of the mouth as with other cardioid microphones. The boom of the microphone can sit comfortably at the corner of the mouth so an unobtrusive appearance is easily achieved. Both the headset and earworn mics feature a boom bendable beyond 360°. Each microphone includes one Interchangeable X-Connector for termination to your wireless system.

Boom Bends 360°	135 dB max SPL	Interchangeable X-Connector
		

-XXX CONNECTOR OPTIONS

- XAK AKG, Audix
- XMP MiPro
- XSH Shure, Line 6
- XAT Audio-Technica
- XSD Sony DWT-B01
- XSK Sennheiser SK, Zaxcom
- XBY Beyerdynamic
- XSE Sennheiser
- XTX Telex
- XLE Lectrosonics

-XX COLOR OPTIONS

-  -BE Beige
-  -BR Brown
-  -BL Black

SPECIFICATIONS

Element:	Back Electret Condenser
Pattern:	Unidirectional, Cardioid
Frequency:	160Hz ~ 14kHz
Sensitivity:	-50 dB 1V/Pa (Nominal Sensitivity ± 3dB at 1kHz)
Maximum SPL:	135 dB SPL
Output Impedance:	5000 Ω ± 30% (at 1kHz)
Operating Voltage:	1 ~ 10 V
Cable Length:	4ft .077in. + connector
Net Weight:	0.6 oz
Colors:	Beige, Brown, or Black
X-Connector Options:	TA3F, TA4F, TA5F, Lockable 3.5mm, Hirose, Lemo-style
Boom Flexibility:	Bendable to 360°
Ear Placement:	Left/Right
Included Accessories:	Windscreen, cable clip, storage box

